

Lighting Device

ROTARY SWITCH ~~FLASHLIGHT~~

B  
Inventor: Kevin McDermott  
Citizen of: United States of America  
Residence: 196 Phillips Drive  
Hampstead, MD 21074  
ph. 410-775-7122

BACKGROUND OF INVENTION

The current invention provides a watertight flashlight with an adjustable intensity that finds application for a wide variety of uses such as scuba divers, auto mechanics and soldiers. Prior art provides a flashlight with a rotary switch offering "ON" and "OFF" positions. It does not provide a momentary "ON" position. The prior art switch is not easily accessible by the thumb of a user. It does not provide a variety of output light modes. The activator or switch is not easily visible to a user making it difficult for a user to know its mode. The prior art design does not provide a means to continuously vary the intensity of the emitted light within a range of intensities. Prior art provides a watertight design with a seal at the switch but no disclosure is made regarding the ability of the prior art seal to release the internal hydrogen gas from its case to avoid a safety hazard. The switch on the prior art design does not include a means to lockout movement to prevent accidental switch activation. The contacts for the switch are part of the case. Therefore, worn or pitted contacts are not easily replaced if they become corroded. Prior art does not provide a means for the lens to assume control of the intensity of the lamp thereby permitting a user with large gloves to operate the light. Prior art does not provide a means to permit the position of the lens to limit the intensity of the emitted light.

## SUMMARY OF INVENTION

Embodiments of the current invention solve the many aforementioned problems of the prior art design. The current design discloses a flashlight with a power control means that is easily activated by the thumb of an operator. Additionally, the operator can easily use his thumb to achieve different intensity levels as well as a momentary "ON" mode. If the operator has gloves and cannot move the activator lever of the current design, he can still use the flashlight and control its intensity by rotating the lens. The flashlight is watertight and remains watertight even if the lens is partially unscrewed to adjust the intensity. An optional lockout is provided to assure that the activator lever does not accidentally energize the lamp during shipping and storage of the flashlight. A two direction seal is provided to permit hydrogen gas to escape the flashlight and avoid an explosion hazard while simultaneously sealing the flashlight against the entry of water.

The present invention describes a flashlight including, a case, a power supply, a light module comprising a lamp and a power control means. The flashlight is capable of a plurality of functions. The power control means usually comprises an activator and an electrical controller. The electrical controller is a switch, rheostat or potentiometer which is activated or controlled by the activator. The electrical controller normally includes a movable plunger which upon a deflection changes a parameter - usually its resistance - of the electrical controller to change the voltage to the lamp. The operator controls the power supplied to the lamp by manually moving the activator

which in turn moves the plunger of the electrical controller and thereby adjusts the electrical controller which regulates the voltage applied to the lamp. The electrical controller employs a plunger which requires a linear movement to change its characteristics. However, other plungers requiring rotary or other movements could also be employed. The activator means is fastened to the case of the flashlight and the electrical controller fastened to the light module. This embodiment is advantageous in that the activator is not electrically connected to or physically fastened to the light module. This permits the light module to be easily removed from the flashlight for repair or when changing batteries. It also permits rapid maintenance as the electrical controller is ~~contained~~ within the light module a component which is easily replaced.

The power control means turns the flashlight "ON" and "OFF". It also permits the flashlight to remain "ON" when unattended. It also permits the intensity to be varied within a range of intensities. It also provides a spring loaded momentary "ON" mode whereby the flashlight automatically extinguishes the lamp when its activating lever is released by the user. The momentary "ON" mode can also be employed by the user to pulse or flash the light or to send a coded signal with the output beam.

If the activator lever of the power control means is positioned at the "ON" position the control of the power to the lamp of the flashlight can be regulated by the position of the lens of the flashlight relative to the case. Thus an operator can regulate the intensity by a movement of the lens. This is desirable for those situations where a user has gloves and cannot easily manipulate the compact activating lever. Additionally, the







and cost considerations can limit the achievable pressure differential between external pressure seal and internal pressure hydrogen release.

Some embodiments of the current invention employ an O-ring seal and achieve a desired pressure differential by configuring and dimensioning the related components of the activator to permit the O-ring seal to change its shape. Other embodiments employ seals of other shapes such as a U seal which includes a configuration which abets a pressure differential.

It is, therefore, an object of this invention to provide a lighting device that comprises an activator which includes a plurality of positions to effect a plurality of intensities.

It is a further object of this invention to provide a flashlight with a range of output intensities from bright to dark controllable by an operator by movement of an activator with his thumb.

It is a further object of this invention to provide a lighting device comprising an activator that comprises a lockout slider that secures the lever of the activator in the "OFF" position and requires an operator to manually move the lockout slider to permit rotation of the lever or energizing of the lamp.

It is a further object of this invention to provide a lighting device including a rotary switch activator that includes a seal that seals the device and prevents water from entering when the device is submerged yet permits hydrogen gas within the device at low pressure to exit the device when the device is not submerged.

It is a further object of the current invention to provide a lighting device comprising a rotary activator whereby the result

A 06947546-101197

resulting  
A ~~FIG.~~ from a rotational position of the lever of the rotary activator can be controlled by a position of another element of the flashlight such as a bezel or lens.

#### BRIEF DESCRIPTION OF THE DRAWINGS

A FIG. 1 is a plan view of flashlight ~~100~~ according to the current invention.

FIG. 2 is a front view of FIG. 1.

FIG. 3 is a partial sectional view taken across line 3-3' of FIG. 1.

FIG. 4 is a front view of the case only from FIG. 2.

FIG. 5 is a right side view of the case shown in FIG. 4.

FIG. 6 is a sectional view taken across the lines 6-6' of FIG. 5.

FIG. 7 is a sectional view of the lens 1 from FIG. 3.

FIG. 8 is a front view of battery B1 from FIG. 3.

FIG. 9 is a front view of the base spring 5 from FIG. 3.

FIG. 10 is a partial sectional view taken across line 10-10' of FIG. 1.

FIG. 11 is a front view of the light module 4 from FIG. 3.

FIG. 12 is a left side view of the light module 4 of FIG. 11.

FIG. 13 is a right side view of the light module 4 of FIG. 11.

FIG. 14 is a perspective view of the rheostat from FIG. 13.

FIG. 15 is a front view of the rheostat of FIG. 14.

FIG. 16 is a schematic of the electrical circuit of the FIG. 1 flashlight.

FIG. 17 is a partial sectional view of the activator of the FIG. 1 flashlight taken across line 17-17' of FIG. 2.



FIG. 18 is a assembly view showing the components of the FIG. 17 activator.

FIG. 28 is a partial front view of the activator similar to FIG. 22 except lens 1 is unscrewed from the case a separation

distance S.

FIG. 29 is a partial sectional view of the flashlight similar to FIG. 23 showing the cam and follower of the activator with the lever in the "ON" position and lens 1 unscrewed from the case separation distance S as shown in FIG. 28.

FIG. 30 is a partial sectional view of the activator similar to FIG. 17 except an external pressure is applied to the flashlight.

FIG. 31 is an enlarged partial sectional view of the activator similar to FIG. 17 except an internal pressure is applied to the flashlight.

FIG. 32 is a partial sectional view of the activator similar to FIG. 17 except the O-ring seal of FIG. 17 has been replaced with a U seal.

FIG. 33 is an enlarged partial sectional view of the U seal portion of the activator shown in FIG. 32 with an external pressure applied to the flashlight.

FIG. 34 is an enlarged partial sectional view of the U seal portion of the activator shown in FIG. 32 with an internal pressure applied to the flashlight.

FIG. 35 is an enlarged partial sectional view of the activator similar to FIG. 17 except the slider for the lockout is shown in the release position.

FIG. 36 is a schematic of an alternate circuit that could replace the circuit shown in FIG. 16. FIG. 36 is similar to FIG. 14 except the rheostat has been replaced by a push button switch of equal size and configuration.

FIG. 37 is a perspective view of a push button switch that could be substituted in the FIG. 36 circuit as a replacement for

the rheostat shown in FIG. 15.

#### DETAILED DESCRIPTION OF THE DRAWINGS

FIGs. 1 thru 31 show a preferred embodiment of the current invention described as flashlight 100. FIGs. 32 thru 35 show some of the possible modifications of the FIG. 1 flashlight which are also disclosed as part of the current invention.

FIGs. 1 and 2 are plan and front views of flashlight 100. Flashlight 100 includes lens 1, case 2 and activator 3.

FIG. 3 is a partial cross-sectional view taken across line 3-3' of FIG. 1. In FIG. 3 batteries B1 and B3 are installed in battery cavity 19A with their negative terminals N1 and N3 facing base spring 5. Coil 38 of spring 5 is designed to maintain pressure against battery B3 throughout the range of movement of lens 1. Batteries B2 and B4 are installed in battery cavity 19B with their positive terminals P2 and P4 facing base spring 5. Coil 39 of spring 5 is similarly designed to maintain pressure against battery B4 throughout the range of movement of lens 1. Thus throughout a range of movement battery rib 17 in case 2 prevents batteries B1 and B3 from falling into battery cavity 19B before batteries B2 and B4 are installed. Base spring 5 constructed of a metallic wire provides an electrically conductive path between the negative terminal N3 of battery B3 and the positive terminal P4 of battery B4. As a result of this connection batteries B1 through B4 are in a series configuration and operate as a single 6 volt battery or power supply PS with its positive terminal at the positive terminal P1 of battery B1 and its negative terminal at the negative terminal N2 of battery B2. O-ring seal 8 is disposed about lens 1 to form a watertight seal.

FIG. 4 is a front view of only case 2 from FIG. 2.

**THE UNIVERSITY OF CHICAGO**

Referring to FIGS. 4 thru 6 case 2 includes: head section 10, offset section 11 and battery section 12 all of which are hollow. Case 2 can be injection molded of a high impact plastic as a single unitary component. Head section 10 includes: interior wall 13, head cavity 14, head opening 15 and thread sections 16A and 16B which are portions of a single continuous internal thread. Battery section 12 is elongated and includes: battery rib 17, base 18, and battery cavities 19A and 19B. Offset section 11 includes: offset cavity 20. Transition wall 21 connects head section 10, offset section 11 and battery section 12 such that they form an integral case 2. Transition wall 21 is substantially perpendicular to elongated battery section 12. Case 2 further comprises activator follower slot 22, activator hole 23, activator O-ring groove 24, activator momentary spring groove 25, activator momentary spring slot 26, activator "ON" wall 27, activator momentary wall 28, activator "ON" stop pin 29, activator momentary stop pin 30, activator lockout slot 31. Case 2 includes longitudinal axis X.

FIG. 8 is a front view of battery B1 from FIG. 3. Battery B1 is typically 1 1/2 volts and includes a positive terminal P1 and negative terminal N1. Battery B1 is similar to batteries B1 through B4 and can be any of a variety of commercial battery





linear manner relative to the deflection of rheostat plunger 51 however linear relationships between the deflection of plunger 51 and the resistance can be employed to accommodate other lamps. Plunger 51 is spring loaded so that absent external forces it automatically returns to its natural extended height H. The spring forces created by rheostat plunger 51 when it is deflected must be balanced by frictional forces in activator 3 to be later described.

FIG. 17 is a partial cross-sectional view of activator 3 taken across line 17-17' of FIG. 2. In FIG. 17 it can be seen that lockout slide 55 and lockout slide tab 55B cover lever opening 53B when the lockout slide is in the lockout position. This prevents dirt from entering the lockout mechanism. Lockout slide 55 continues to prevent dirt from entering the lockout mechanism even when in the release position to be later described in FIG. 35.

FIG. 18 is an assembly drawing of the FIG. 17 activator 3. Looking at FIGs. 17 and 18, activator 3 includes a lever 53, screw 54, lockout slide 55, lockout spring 56, activator O-ring seal 57, momentary torsion spring 58, cam 59 and follower 60. Looking at FIGs. 2, 4, 17, and 18, assembly of activator 3 is accomplished according to the following procedure. Place compression type lockout spring 56 in lockout slider opening 55A and with lockout spring 56 compressed insert lockout slide 55 in the underside of lever 53 in U shaped lever slot 53A such that lockout slide tab 55B passes through lever opening 53B. Place activator O-ring seal 57 in activator O-ring groove 24 of case 2. Place momentary spring 58 in activator momentary spring groove 25 of case 2 with momentary spring lower tab 58A in activator momen-







lever 53 in the "OFF" position. He would also have to manually move lockout slide 55 out of lockout slot 31 before he could light flashlight 100. The lockout feature of the current invention permits flashlight 100 to be stored with other camping gear or in a knapsack while in the full "OFF" position without accidentally being turned "ON".

If the operator rotates lever 53 past lockout slot 31 lockout slide 55 will rub along and rotate past momentary "ON" wall 28 and then upon continued rotation and as a result of forces from compressed lockout spring 56 move into momentary slot 28A. This movement of lockout slide 55 will - due to the large size of momentary slot 28A - not prevent further counterclockwise rotation of lever 53. At this rotational position of lever 53 further counterclockwise rotation of lever 53 will wind up momentary torsion spring 58. Eventually, upon further counterclockwise rotation of lever 53 second lever side 53H will contact momentary stop pin 30 to prevent further rotation of lever 53. This represents the full momentary "ON" position. If the operator of the flashlight releases lever 53 it will - due to the previous winding up of momentary torsion spring 58 - automatically rotate lever 53 clockwise until torsion spring 58 returns to its natural state. Lever 53 will not automatically rotate back to the full "OFF" position even when urged to do so by the previously wound momentary torsion spring 58 because slider 55 which has been extended by lockout spring 56 will be contacted by momentary wall edge 28B. If the operator wishes to move lever 53 to the full "OFF" position, he will be required to move slider 55 as previously described in the direction of slider arrow 55D. If lever 53 is in the momentary "OFF" position lamp 44 will generally be

extinguished as it is when lever 53 is in the full "OFF" position. The momentary "OFF" position of lever 53 is designed to be at angle A to the longitudinal axis of flashlight 100 so that an operator can use his thumb to easily apply to lever 53 a force which will create a torque about screw 54 to rotate lever 53 counterclockwise to create a flashing effect from lamp 44 by a means to be later described. Additionally, since lever 53 returns automatically to the momentary "OFF" position the operator is not required to pull it back with his thumb. Also if the operator is a soldier and he accidentally drops flashlight 100 it will automatically turn off avoiding a possible breach in security. Lever 53 additionally includes a lever thumb pad 53J which serves to permit the operator to easily move lever 53 with his thumb. The thumb pad 53J is usually a greater distance from the case 2 than lockout slide tab 55B to protect lockout slide tab 55B from accidental movement.

Having previously discussed the various positions of lever 53 relative to the exterior of flashlight 100, it is now appropriate to discuss how each position of lever 53 affects the intensity of lamp 44. In that regard first it must be realized that lever 53 is securely attached to cam 59 employing cam key 59D. Thus rotation of lever 53 causes cam 59 to also rotate. Rotation of cam 59 results in a linear movement of follower 60 within activator follower slot 22 and substantially parallel to longitudinal axis X of case 2. Follower 60 in turn pushes on plunger 51 of rheostat 48 changing the deflection of plunger 51 and thereby changing the resistance of rheostat 48 to regulate the voltage applied to lamp 44 and vary its intensity. The details of this process can be understood by looking closely at

FIG. 19 and also at FIGS. 1 thru 19. FIG. 19 is an enlargement of cam 59 and follower 60 portion of FIG. 10. In FIG. 19 cam 59 is in the "OFF" position of lever 53 as shown in FIG. 2. In this position cam ramp "OFF" point 59F of cam ramp 59E is contacting follower pin bottom 60D of follower 60 thereby pushing follower pin 60 towards rheostat plunger 51 where follower pin top 60E is just contacting rheostat plunger face 51A. In FIG. 19 rheostat plunger 51 has therefore not been deflected and is at its natural height H. Rheostat 48 is therefore at infinite ohms across rheostat terminals 49 and 50 resulting in zero voltage across lamp 44.

Cam ramp 59E also includes: a momentary "OFF" point 59G, cam ramp "ON" portion 59H and cam ramp momentary "ON" portion 59J.

Referring to FIGS. 20 and 21, lever 53 is in the "OFF" position and cam 59 is positioned as previously described in FIG. 19. Looking at FIGS. 22 and 23, lever 53 is in the "ON" position with cam ramp "ON" portion 59H contacting follower pin bottom 60D of follower pin 60 thereby pushing follower pin 60 towards rheostat plunger 51 where follower pin top 60E is pushing rheostat plunger 51 and deflecting it to deflection D2. At this deflection rheostat 48 is at approximately 2 ohms resulting in almost six volts across lamp 44 making lamp 44 at approximately full brightness. It can be seen from the gradual curve of cam ramp portion 59H that as lever 53 is rotated from the "OFF" position of FIG. 20 to the "ON" position of FIG. 20 rheostat plunger 51 gradually changes its location starting at no deflection and at its natural height H to full deflection D2. If lever 53 were only partially rotated towards the "ON" position rheostat plunger 51 would only be partially deflected such as to a deflection D1

resulting in rheostat 48 having a resistance of 6 ohms resulting in approximately 4.5 volts applied to lamp 44. This applied voltage would light lamp 44 at a reduced intensity. In a similar fashion lever 53 could be moved to and left at numerous positions between the "OFF" and "ON" positions to apply numerous voltages to lamp 44 and thereby light lamp 44 at numerous intensities. As lever 53 is slowly rotated from "OFF" to "ON" the voltage applied to lamp 44 slowly increases. The rate of voltage change depends in part upon the shape of cam ramp portion 59H. A steep slope will effect a rapid change in the intensity of lamp 44 in response to a defined rotation of lever 44. Generally, the slope of cam ramp portion 59H is gradual so that the operator can easily move lever 53 at a rate of rotation which will slowly change the intensity of lamp 44.

Referring to FIGs. 24 and 25, lever 53 is in the full momentary "ON" position with cam ramp full momentary "ON" portion 59J contacting follower pin bottom 60D of follower pin 60 thereby pushing follower pin 60 towards rheostat plunger 51 and deflecting it to deflection D2. This is the same deflection distance as found in FIG. 23 and therefore lamp 44 is at the same intensity as described in FIG. 23 with lever 53 in the full "ON" position. This is an acceptable design however some users may wish the flashlight to emit at different intensities at the full "ON" and the momentary "ON". This is easily achieved by adjusting the contours of the cam ramp momentary "ON" portion 59I and the cam ramp full "ON" portion to create different deflections of rheostat plunger 51. It should be noted from FIG. 19 that the contour of cam ramp momentary "ON" portion 59I comprises a steeper





flashlight. In that regard refer to FIGs. 17, 18, 30, and 31. FIGs. 30 and 31 are enlarged views of the sealing portion of activator 3. After assembly as disclosed in FIG. 18 and with an external water pressure PE of up to one hundred pounds per square inch applied to flashlight 100 activator 3 appears as shown in FIG. 30.

In FIG. 30 activator O-ring seal 57 is pressed into the activator O-ring groove 24 by the activator lever bottom face 53E such that a watertight seal is made ~~about~~ the activator O-ring seal 57 and both activator O-ring groove 24 and cam shaft 59C at all points typified by O-ring groove seal point 24A. Clearance C resulting from designed tolerances in the components of activator 3 appears between cam 59 and case 2 where the clearance does not degrade sealing.

Looking now at FIG. 31 which is identical to FIG. 30 except the external water pressure PE has been replaced with an internal hydrogen gas pressure PI of a minimal value such as ten pounds per square inch. In FIG. 31, the internal pressure PI shifts lever 53 such that the clearance C now appears between lever bottom face 53E and activator O-ring seal 57. Activator O-ring seal 57 is also moved by internal pressure PI so that it is no longer pressed into activator O-ring groove 24. In this configuration, due to the taper of activator O-ring wall 24B of O-ring groove 24, the hydrogen gas can escape case 2 past activator O-ring groove seal point 24A. This design differs from classical prior art O-ring seals because they do not provide clearances which release hydrogen gas ~~passed~~ the seal as a result of pressure reversal.

FIGs. 32, 33, and 34 disclose an alternate method to seal



activator 3. In this alternate embodiment in place of the O-ring seal 57 disclosed in similar drawings FIGs. 18, 30, and 31 an activator U-ring seal 57A has been substituted. No special clearances between the activator components are shown or required other than to permit free movement of the components. Even without special clearances hydrogen gas will pass between these components freely if a seal is not present.

A Looking at FIG. 33 which is identical to FIG. 32 except an external water pressure PE is applied to flashlight 100 one sees that the external pressure will enter activator O-ring groove 24 and spread the legs 57B of the U<sup>ring</sup> seal 57A such that they seal against the activator O-ring groove wall 24B.

A Now looking at FIG. 34 which is identical to FIG. 32 except an internal hydrogen pressure PI is applied it can be seen that the seal has been broken. In FIG. 34 the internal pressure moves the flexible legs 57B of the U<sup>ring</sup> seal 57A such that they move away from the activator O-ring groove wall 24B and cam shaft 59C to permit the hydrogen gas to escape. U<sup>ring</sup> seal 57A is flexible and will break the seal without a movement of other components of activator 3. The sealing means disclosed in FIGs. 30, 31, 33, and 34 represent only two of numerous methods to create a water-tight light which still permits the hydrogen gas to escape. The sealing method permitting the release of the hydrogen is efficiently incorporated into the activator but could also be supplied as a separate part of flashlight 100.

FIG. 35 is similar to FIG. 17 except the lockout slider is shown moved by the operator using lockout slide tab 55B to permit release of the lockout and rotation of lever 53. In this configuration lockout spring 56 is compressed. Also activator "ON"

wall 27 can freely pass through lever groove 53F. Finally lock-out slide 55 blocks the entry of dirt into lever opening 53B preventing the entry of dirt into the lockout mechanism. In fact all components of activator 3 are designed to preclude dirt from getting into the mechanism. This assures reliability even in dirty environments.

FIG. 36 is a drawing of an alternate circuit which uses a spring loaded momentary "ON" switch 48S in place of rheostat 48. FIG. 37 is a front view of switch 48S. It includes switch first terminal 49S, switch second terminal 50S and switch plunger 51S. Plunger 51S has a natural height H at which it is "OFF". Upon a linear axial movement M to a deflection D2 of switch plunger 51S switch 48S turns "ON". Switch 48S can be substituted for rheostat 48 and reduce the cost of flashlight 100 however, lamp 44 will only have one intensity.

Having now fully set forth the preferred embodiments and certain modifications of the concept underlying the present invention, various other embodiments as well as certain variations and modifications of the embodiment herein shown and described will obviously occur to those skilled in the art upon becoming familiar with said underlying concept.

It is to be understood, therefore, that within the scope of the appended claims, the invention may be practiced otherwise than as specifically set forth herein.

What is claimed is:

1. A lighting device including:  
a case including a first opening;  
a power supply disposed within said case;  
a light module means, disposed within said case comprising a